

SafeQ integration

Denne vejledning har til formål at forklare, hvordan Studiz integreres med SafeQ print-system, således studerende og ansatte kan anvende Studiz app'en til at få adgang til institutionens printere samt printe på disse.

Kontakt jeres Studiz repræsentant for at få åbnet for denne funktion.

Stamdata

Under funktionen med skolens navn i Studiz admin modul, klikkes der på "stamdata", hvor det er muligt, at tilføje skolens <u>IP-adresser</u>, hvilket er det som afgøre, hvorvidt **print-service** bliver tilgængeligt under menu-punktet "studiekort/medarbejde-ID" i app'en. Systemet tjekker således hvorvidt den enkelte er på institutionens netværk, og viser kun print-service når dette er tilfældet. Base url er url adressen til den server der kører skolens SafeQ system.

QR-kode og listevisning

Inde i SafeQ administrationsmodul, kan man print en QRkode hvor hver enkel device (printer). Det er denne kode, der scannes via Studiz app'en, for på denne måde, at fortælle SafeQ systemet, at man ønsker tilgang til den specifikke printer.

Som et tillæg hertil er det også muligt at tilføje institutionens printere, sådan ansatte og studerende får en liste at vælge fra. Ønskes dette, så informer jeres Studiz repræsentant. Der vil så blive mulighed for at tilføje og redigerer disse under "stamdata".



Betalingssystem

Integration med SafeQ's print-betalingssystem er under udvikling.

Vi hører også mægtig gerne fra dig, hvis du har spørgsmål, ønsker til funktionalitet eller ideer til forbedringer/integrationer.

Mvh. Lasse Tindbæk CEO Tlf. **29408339** E-mail: <u>It@studiz.dk</u>



Add card with Uni-login in SafeQ

1. Vælg "Users" og "edit"

$\dot{\cdot}$	Users > Users				=	System Administrator admin
Dashboard	Users Cost centers	Roles				
Int Reports	+ ADD NEW ITEM + IN	IPORT USERS FROM LDAP				ACTIONS - VIEWS
Devices	Username		Surname		Cost center	t x
📎 Billing	Card		First name		Role	5 ×
🛓 Users	User note					
② Rules	Q SE	ARCH CLEAR				
Scan workflows						
🌣 System	Username 🔨	Surname, First name		Cost center		Email
	admin	Administrator, System		0 - Default cost center		F
	stormtindbaek	User, Test		1 - Paying users		
	test	Test, Test		1 - Paying users		
					0	He H 1/1 H ₩

2. Scroll ned til "Cards" og vælg "+ Add new card"

$\dot{\cdot}$	Users > Users > User	System Administrator admin
Dashboard	Users Cost centers Roles	
Lal Reports	PIN codes	+ Add new PIN
Devices	**** 00	8
🗞 Billing	Cordo	▲ Arld pow pard Basic ●
Subsers	Cards	Billing
② Rules		Properties III
Soon		PIN codes O
workflows	****h	û Cards 💿
System	****1	🛍 Roles 💿
	Mohile Terminals	Aliases III
	Woblie Terrinitais	Billing codes
	User does not have any Mobile Terminals activated.	
	Roles	+ Add role

3. Indtast personens UNI-login brugernavn

$\dot{\mathbf{v}}$	Users > Users > User	Add new card	× System Administrat	or
	Users Cost centers	Card number •		
	PIN codes			
	****		CLOSE SAVE NEW CARD	
	Cards		+ Add new card Basic	
	Cards		Billing	
	Card number		Properties	
	****		PIN codes	
scan vorkflows	****h		Cards	
	****1		Coles Roles	
			Aliases	
	Mobile Terminals		Billing codes	
	User does not have any Mo	bile Terminals activated.		
	Roles		+ Add rele	



AD import af Unilogin som Cards I SafeQ

Lige en hurtigt trinopdater at de trin som jeg har gjort for at få Unilogin ind som Cards i SafeQ

Fra SafeQ Dashboard.

1. Ind <u>på "System"-</u>fanen



2. LDAP-integration



3. Advanced settings





4. Under Users schema har jeg indsat variablen "sAMAccountName" _som har vores elevers Unilogin og kopier den ind i feltet "Attributes containing cards/PINS"

Users schema		
Import users	Enable	~
Attribute containing username	sAMAccountName	
Do not include domain in username	None	~
Attributes containing aliases	mail, extension Attribute 2	
Attribute containing user first name	givenName	
Attribute containing user surname	sn	
Attribute containing user email	mail	
Check username uniqueness	Disable	~
Attribute containing user role (membership)	memberOf	
Attributes containing cards/PINs	sAMAccountName	
Card number conversions		
Card separator		
Delete all the user's cards when a user's account is deactivated	Enable	~
Attribute containing PIN code		
PIN code conversion		

5. Derefter "Save changes" og "sync now"

SAVE CHANGES

6. Herefter kommer Unilogin fint ind som Card i SafeQ

Cards	+ Add new card
Card number	
afve55a7	ŭ



Troubleshooting

- 1. Vær opmærksom på, at dine printere skal være kompatible med Skyprint fra SafeQ
- 2. Terminal mode på hver terminal skal være sat til 2nd. Gen.

Accounting method	Device dependent accounting	~	
	Batch accounting		
Reporting cost center ID	0 (Default cost center)	•	
Terminal			
Installation status	Terminal installed		
Terminal mode	Native YSoft SafeO Terminal Application - 1st Gen.		
Authentication method	YSoft SafeQ Terminal Application - 2nd Gen.		
QR code	Show QR code		
	Allow public user		
Direct printing			